

AD-50

Proximity Door Controller



Features:

- Door Bell function.
- Back-lit 12-key Keypad.
- 400 Card Holders(can upgrade to 3,000) .
- 2 Relays for Door Lock & Alarm.
- 2 Sensors for Push Button & Door Sensor.
- System halts for 25 Sec. after 5 attempts by invalid card.
- 3 modes to open the door: Card / PIN / Card+PIN.
- With Access Control On/Off function.
- Tri-color (Red/Green/Orange) LED X 1; Buzzer X 1.
- Can set Door Sensor NO/NC mode.
- Can set valid Card Reading Digits.
- Stand-alone design; can work without PC.
- Delicate & compact design.

Specification:

| | |
|---------------------|-------------------------------|
| Access interfaces | EM 125K HZ/Keypad |
| Input Sensor | 2 (Door Sensor & Push Button) |
| Output Relay | 2 (Door Lock & Alarm) |
| Indicator | 1 LED(Red/Green/Orange) |
| Keypad | 12 Keys |
| Audio Indicator | Buzzer |
| Reading Range | 10cm(max) |
| Power Input | DC12V@250mA |
| Power consumption | 2.5W |
| Working Temperature | 5°C~55°C |
| Relative Moisture | 20%~90% |
| Measurements | 124mm(L)X75mm(W)X23mm(H) |
| Weight | 150g |